## harbus® HM Power



## Male connectors angled, with press-in termination


9,05±0,05


10,7±0,05

12,35±0.05

7,4 ±0,05

Identification	Number of contacts	Contact length [mm] termination side	Part number	Contact loading
Connector with same sized contacts	4	2.8	17 61 004 2102	Position $-\frac{1}{4}$ $\frac{1}{3}$ $\frac{1}{2}$ $\frac{1}{1}$
Connector with same sized contacts	4	2.8	17 61 004 2103	Position $-\frac{1}{4}$ $\frac{1}{2}$ $\frac{1}{1}$
Connector with leading/lagging contacts OBSAI configuration	4	2.8	17 61 004 2101	Position $-\frac{1}{4}$ $\frac{1}{2}$ $\frac{1}{1}$
Connector with leading contact	4	2.8	17 61 004 2104	Position $-\frac{1}{4}$ $\frac{1}{3}$ $\frac{1}{2}$ $\frac{1}{1}$
Contact dimensions [mm] Connector dimensions [mm]				
$XL^{2}$ $L$ $H$ $S$ $\frac{9,65\pm0.05}{3}$ $\frac{3\times 3(:9)}{3}$ $\frac{3\times 3(:9)}{3}$				





Ø1,5±0,05 1)

4,5

2x ⊕ 0.05}


3x 3 (=9)

3

11,9

14,35 max. 4.5 2,2 min. 13,3±0,1 (View magnified)

Board drillings



2±0,05 m m

(6=)

З×

03 04

harbus" HM Power